



Specifications Philips LED Batten
CoreLine White 18W/29.5W
2500lm/4100lm - 830-840 CCT | 120cm
- Replaces 2x36W

[View Product](#)

General Information

| | |
|--------------------------|------------------------------------|
| SKU | 255171 |
| EAN | 8720169768406 |
| Manufacturer Code | 8720169768406 |
| Brand | Philips |
| Manufacturer Name | BN126C LED25S_41S/830_40 PSU L1200 |
| Any Lamp all-in warranty | 5 Years |
| Average Lifetime (h) | 50000 |

Technical Information

| | |
|-----------------------------|----------------------------------|
| Technology | LED Integrated |
| Replaces (Watt) | 2x36 |
| Wattage | 29.5W |
| Voltage (V) | 220-240 |
| Dimmable | Not Dimmable |
| Colour of Light | White |
| Colour Code | 865 Daylight |
| Colour temperature (Kelvin) | 3000 Warm White, 4000 Cool White |
| Colour Rendering (Ra) | 80-89 |
| Light colour options | Single Color |
| Luminous Flux (Lumen) | 4100lm |

| | |
|--------------------------|------------|
| Luminous Efficacy (lm/W) | 140 |
| Power factor | >0.90 |
| Product Type Category | LED Batten |

Fixture Information

| | |
|------------------------|------------------------|
| Mounting Method | Surface, Ceiling |
| Fixture Connection | PI [Push-in connector] |
| IP-rating | IP20 |
| Impact Protection (IK) | IK04 - 0.50 joule |
| Housing | Plastic |
| Colour of the Fixture | White |
| Emergency Lighting | No Emergency Unit |
| Series | CoreLine |

Dimensions

| | |
|-------------|------|
| Length (mm) | 1135 |
| Width (mm) | 65 |
| Height (mm) | 65 |

Sensor Information

| | |
|----------------|-----------|
| Type of sensor | No Sensor |
|----------------|-----------|

Why Any-lamp?

 Order from the **largest lighting specialist** in Europe  **Customised** quotation

 Up to **7 years warranty**  **Easy** return process